

# DSP-7 Vehicle Detector

*A New Plug and Play "Micro" Detector  
All this and a 5-Year Warranty too!*

## OPERATION

At last a vehicle detector which will operate on any voltage from **10 to 30 Volts AC or DC**.

The DSP-7 detector adds yet another new dimension of simplicity to vehicle detectors. This patent pending detector has been specifically designed to handle parking, drive-through and access control applications.

This vehicle detector incorporates all of the quality features of our other detectors while eliminating the switch options that we find are confusing and not necessary for most applications. The detector's small size and lack of any switches or dials becomes the industry's first plug-in "Plug-and-Play" detector.

The DSP-7 is preset to the normal sensitivity level used in parking/access control applications and tunes itself to the best operating frequency. It has built-in sensitivity compensation if the installation should have very large loops or long lead-in runs.

Environmental conditions are constantly compensated with the DSP-7's *HYPERTRACK* software

## FEATURES

**Loop Size** - Works on any in-ground inductive loop from 20 to 1500  $\mu$ H.

**Indicators** - Separate Power/Fail and Detect LEDs.

**Detect Memory** - Power interruptions of short duration are ignored. If power fails for approximately 1½ seconds or less the detector "remembers" a vehicle.

**Sensitivity** - Automatic - compensates for large loops and long lead-ins.

**Outputs** - Both N.O. (closes for detect) and N.C. (opens for detect) outputs.

**Output Relay Ratings** - 1A at 125VAC General use, 1A at 30 VDC resistive.

**Loop Failure** - The green power indicator flashes slowly if the loop circuit is open and quickly if the loop circuit is shorted. This detector will output a "Detect" for either of these loop failed conditions.

**Phone:** (866) 395-6677 (Toll Free Sales)  
**FAX:** (510) 490-4111



**Power** - 10 to 30 Volts AC or DC, 25 mA max.

**Size** - Height: 1.52" Width: 2.9" Depth: 1.56"

**Connector** - Removable 7 position terminal block. Pin assignments are:

- 1 - Output relay (N.C. - opens for detect)
- 2 - Output relay common
- 3 - Output relay (N.O. - closes for detect)
- 4 - Power common
- 5 - Power in (10 to 30 Volts AC or +DC)
- 6 - Loop input
- 7 - Loop input

**Operating Temperature** - -35°F to 165°F (-37°C to 74°C)



*Stuck in traffic for over 30 years!*

**Phone:** (925) 837-1884 (Technical Help)  
**Web Site:** [www.diablocontrols.com](http://www.diablocontrols.com)