




**WATCHMAN**<sup>®</sup>  
Your Virtual Security Guard

**W410**  
model

## Advanced Telephone Entry System



**Part Numbers:**  
AA1TP VZN  
AA1TP ATT



## W410 FEATURES

- Gate can easily be controlled from app
- New low cellular plans *(with or without photos)*
- Customer self-activation
- 1 native 26-bit Wiegand port
- NEW: 5,000 local codes and 64,000 non-local codes
- Cameras take photos on access attempts and on demand
- All transactions and photos stored on TrueCloud portal

**NEW**  
**Watchman WXP\***  
Wiegand Expansion Panel  
& Door Controller  
for Watchman

\*See WXP sheet for details

## W410 EXCLUSIVES

- Calls up to 9 telephone numbers in 3 tiers
- Verizon or AT&T LTE service *\*No VoIP fees required*
- Ships with both AT&T & Verizon SIM cards
- Voice Mail Intelligence – VMI  
*System ignores call when reaches voice mail and continues call tree*
- Prop open notification *If gate is left open more than 3 minutes*
- TrueCloud™ web portal for administration

### EXCLUSIVE External Camera Options\*

- Single external camera

#### Photos

- Taken on entry transactions and on demand
- Cloud-stored still photos

#### Video

- Pixel activated video stored on SD card
- Recording w/6-second pre-record



 **cellgate**

powered by:

\*See external camera sheet for more details

1.855.MY.GATES

cell-gate.com



## W410 Advantages

- Value-priced, feature-rich price point
- Choose desired rate plan (with or w/out photos)
- Convenient call group management
- Voice Mail Intelligence (VMI) = Fewer stranded visitors
- Time/date restrictions for Wiegand credentials
- Control gates/doors on demand or on a schedule
- Manage multiple devices via CellGate TrueCloud



## SPECIFICATIONS

### External Camera Options - limit 1 per W410

- Bullet Cameras**
- 4mm Fixed Focal Lens
  - 5-64mm Varifocal Lens
  - 2.8-12mm Varifocal Lens
- Dome Camera**
- 3-10.5mm Varifocal Lens

### 1 Built in Camera: 3mm

### Internal Camera Angles:

- Horizontal: 120°
- Vertical: 65°

### Power Consumption (12v DC):

275mA (daytime), 330mA (night)

### External Camera Power Consumption:

- Bullet Cameras:**
- 4mm Fixed Focal Lens:  
Max Consumption-Day = 180mA Night = 400mA
  - 5-64mm Varifocal Lens:  
Max Consumption-Day = 180mA Night = 400mA
  - 2.8-12mm Varifocal Lens:  
Max Consumption- Day = 195mA Night = 480mA
- Dome Camera**
- 3-10.5mm Varifocal Lens:  
Max Consumption-Day = 195mA Night = 480mA

### 1 Wiegand Expansion Port (26 bit): 12 volt

### 2 Relays:

Contact rating: .5A @ 125v AC, 2A@30v DC  
Switching voltage: 250v AC, 220v DC  
Switching current: 2A

### 2 Digital inputs

### IP65

### Operating Temperature

-20°C - 55°C | -4°F - 131°F

### Dimensions (excluding antenna)

Height- 8.3" (211mm)  
Width- 6.4" (163mm)  
Depth- 5.5" top (140mm), 4.7" bottom (120mm)

### Cellular Technology/Networks

4G/LTE: Verizon and AT&T

### Included in box

Watchman W410  
Power supply - 5A  
Magnetic switch  
Installation manual & user manual

### Antenna Options

L-bracket  
Directional panel

## Dealer Benefits

- Easy 6-wire installation  
without external camera
- End-to-end support
- Cellular carrier and signal strength verification
- Ships with live SIM  
Verizon or AT&T
- Easy system and feature testing
- New Pepwave router upgrade  
Improved analysis for cellular troubleshooting





## Web Portal

### Manage All Your CellGate Devices on One Dashboard

- Hosted by Microsoft Azure
- Event logs of all transactions
- Photos with access transactions (with photo rate plan)
- Create access credentials with date/time restrictions
- Manage push notifications
- Administrative login privileges

## Cellgate App

- NEW: User can create access codes from the app
- Gate/doors can be opened or held open from anywhere
- Take photos on demand from internal and external cameras (with photos rate plan)
- Review historical photo and access credential use info
- Receive prop-open notifications w/ gate status



App Available at  
App Store and Google Play

